

SIMULATION OF BUCK CONVERTER USING SIMULINK AND SPICE TOOL

Dr.E Venkatesh¹, M.Vandhana², S.Tejaswini³, P.Komali Keethana⁴¹Assistant Professor, Dept. of EEE, Malla Reddy Engineering College for Women, Hyderabad,^{2,3,4}Research Student, Dept. of EEE, Malla Reddy Engineering College for Women, Hyderabad

This article looks at how the power converter designer can use the system-level and detailed models together to enable exploration of the design space and also achieve high confidence in the results. An example of this process will be shown using MathWorks system-level modelling tools Simulink® and Simscape™ with detailed SPICE subcircuits representing Infineon Automotive MOSFETs.

Introduction

During the development of electrical power converters, numerical simulations are typically used during the concept and feasibility study. The simulation models need to include both the analog circuit and the corresponding digital controllers. Examples of the design questions that models can help answer include:

Which topology should be used?

- For a given topology, what performance can be achieved?
- What PWM switching frequency should be used?
- What values and ratings are required for the passive components?
- What kind of power switch should be used:
 - type (like MOSFET or IGBT or BJTs)?
 - technology and voltage ratings (like Infineon's OptiMOS™ or CoolMOS™) and materials (like Si or SiC or GaN)?
- What are the requirements on the gate driver circuits including minimum required dead-time?

Finally, based on previous assessments:

- System efficiency and component losses may be estimated, and subsequently a suitable cooling system can be developed;
- The trade-off of system efficiency with EM compatibility can be investigated. Switching losses and EMI are both dependent on switching frequency and power switch slew rate.

SPICE simulation tools are the go-to solution for circuit designers. However, the design steps described depend on being able to simulate the power converter in reasonable time. Circuit simulation tools like Simscape™ Electrical™ have simple device models that are essentially ideal switches plus tabulated switching losses which meet this efficient simulation need. Moreover, tight integration with Simulink® means that the digital controller is also included in the simulation with no need for co-simulation. However, the ideal switch assumption creates some uncertainty for the later design steps focused on determining efficiency and fine-tuning the design. This uncertainty can be addressed by using detailed SPICE device models developed by the component manufacturer. In this paper, a process is defined that enables fast exploration of the design space whilst also capitalizing on the detailed foundry SPICE component models. Central to the process is making use of multiple models with differing levels of fidelity, matching the model to the specific design question to be answered. Also important is the use of low-fidelity levels to pre-initialize detailed simulation models thereby reducing initialization time.

Buck converter design example

A 48V/12V DC/DC step-down buck converter shown in Figure 1 is used as the example in this paper. A buck converter steps down the input voltage (V_{IN}) to a lower-level output voltage (V_{OUT}), and the main equation characterizing its behavior is given by:

Equation 1

$$d = \frac{V_{OUT}}{V_{IN}} \Rightarrow V_{OUT} = d * V_{IN}$$

where d represents the duty cycle of the high side power switch (HS_SW). The duty cycle of the low side power switch (LS_SW) is given by d' defined by:

Equation 2

$$d' = 1 - d$$




Figure 1: Structure of buck (Step-Down) DC/DC power converter

Based on the reference voltage (V_{ref}) and measured output voltage (V_{meas}), the discrete-time proportional plus integral voltage controller calculates required duty cycle (d).

Infineon SPICE MOSFET model

SPICE ("Simulation Program with Integrated Circuit Emphasis") simulators are the most commonly-used technology for analog circuit simulation. Therefore, as de-facto industrial standard, many semiconductor manufacturers develop SPICE models of their products to support circuit design.

Infineon's portfolio of automotive qualified OptiMOS™ power MOSFETs offer benchmark quality in a range from 20V–300V, diversified packages and an $R_{ds(on)}$ down to 0.55 mΩ. Structure of typical Infineon's SPICE model of MOSFET is shown on Figure 2. This behavioral MOSFET model [1] describes both the electrical and thermal characteristics of the power switch.




Figure 2: Schematic of Infineon's SPICE MOSFET model structure

The model reflects that current flowing through the MOSFET causes changes in semiconductor temperature which, in turn, influences the MOSFET electrical parameters such as charge carrier mobility, voltage threshold, drain resistance, gate-drain capacitance and gate-source capacitance. Referring to Figure 2, thermal behavior is modeled in the following way: a current source (P_v) representing MOSFET dissipated power injects the heat into the PN-junction (T_j), and that heat is then propagated all the way through MOSFET package to the case (T_c). The thermal dynamics is modeled as a Cauer network made up of lumped thermal resistances (R_{thj}) and thermal capacitances (C_{thj}). By means of analog simulation of the thermal model, the optimum cooling/heat sink (R_{thHS} and C_{thHS}) can be determined for given design parameters like load current, maximum allowed junction temperature (T_j), ambient temperature (T_{amb}) and thickness/number of PCB layers (R_{thPCB} and C_{thPCB}).

Importing a subcircuit into Simscape

Simscape [5] from MathWorks provides a block diagram environment to model multi-domain systems, including electrical, mechanical, magnetic and thermal aspects. The accompanying Simscape language expresses the underlying physics using differential equations, associated algebraic constraints, events and mode charts.



Figure 3: Infineon's Automotive MOSFET IAUT300N08S5N012 in TOLL (PG-HSOF-8)

Simscape Electrical™ [6] is able to import a targeted set of SPICE device models, such as MOSFETs, into an equivalent Simscape language implementation [7]. Simscape's tight integration with Simulink then enables simulating both the digital controller and the analog electronics with a single solver, this resulting in a more efficient simulation than co-simulation between different simulation tools.

The SPICE model import capability is used to import the Infineon IAUT300N08S5N012 [2][4] device (shown on Figure 3) into Simscape. Once imported into Simscape, some minor edits were made to the Simscape code to provide access to the Cauer model states from the published block. Providing customized access to the internal states is needed for the initialization process.

Simulation workflow

Having imported the Infineon device into Simscape, the next step is to create a Simulink model of the complete converter including the imported Infineon devices, remaining analog components and the controller. This is shown in Figure 4.

The controller is implemented using Simulink discrete-time library blocks, and the complete model is simulated using a variable-step solver so that the faster time constants associated with parasitics and the MOSFET charge model are accurately captured. The simulation

time for one controller PWM cycle is 2.3 seconds on an Intel® Core™ i7-9700 CPU @ 3.00 GHz running MATLAB version R2021b. This is fast enough to analyze circuit performance at current operating state, but not to assess circuit sensitivity to design parameter sweeps or to directly optimize the circuit parameters. Furthermore, it is not fast enough to simulate to a periodic steady state which, given a thermal time constant of approximately 10 seconds, equates to 200,000 20 kHz PWM cycles.




Figure 4: Detailed model of the buck converter

To address the need to explore the design space efficiently, a system-level version of the buck converter model created. For this, the imported MOSFET device models are replaced with ideal switches with fixed on-resistance set to the datasheet $R_{ds(on)}$ value. This is shown in Figure 5. Some of the faster parasitics are also omitted, such as the MOSFET lead inductances. This system-level model is fixed temperature, the user setting an appropriate $R_{ds(on)}$ value for the assumed junction temperature. The model takes around 0.05 seconds to simulate one PWM cycle, 46 times faster than the detailed model. As there are no thermal time constants, the slowest dynamic is now associated with the voltage regulation and is of the order of 5 ms or 100 PWM cycles. Hence simulation to steady state takes approximately 5 seconds.

With this simulation performance, the system-level model can be used to thoroughly explore the design space and optimize the controller. With the main design decisions made, the final step is to validate the design using the detailed simulation model that makes use of the Infineon MOSFET models. This validation is typically reported at a set of operating points defined by load power and ambient temperature. However, we have seen that to simulate the detailed model to steady state requires 200,000 PWM cycles which is not practical if each cycle takes 2.3 seconds to simulate.



Figure 5: System-level Simulink model of the buck power converter

To initialize the detailed model at a specified operating point, an iterative approach involving multiple models is proposed. Overall, the idea is to separate out slower time constants into separate models that run faster. Before explaining in more detail, one more model is required which is one that models the MOSFET and environment thermal states only. This is shown in Figure 6.

implement two or three MOSFETs in parallel for both the high-side and low-side switches. The important thing to note is that there can be a high-level of confidence in this result given that the validated foundry SPICE MOSFET models were used to generate them and that the results are for the actual circuit. This gives a higher-level of confidence than the sometimes-used alternative based on data-sheet plots of on-state and switching losses for a representative test circuit.




Figure 8: Proposed simulation flow for switching power converters

A summary of the overall process followed is shown in Figure 8. The process is implemented as a MATLAB® script which can be downloaded from MathWorks File Exchange [3]. The script takes four minutes to run and produce the results in Figure 7. For comparison, it was determined that running the non-linear model from an non-initialized state to get to the same result takes of the order of a day.

Conclusions

It has been shown how detailed SPICE foundry semiconductor models can be used in an application circuit model to make high-confidence predictions about expected circuit performance. The challenge of initializing a model with widely varying time constants and with a periodic steady state has been tackled with a two-pronged approach. Firstly, avoidance of slow co-simulation is achieved by importing SPICE subcircuits into Simulink, and solving the complete analog system plus controller using a variable-step solver. Secondly, the steady state is found by using multiple models with differing fidelity levels with a simple iterative scheme. The end result is an end-to-end design and simulation capability that is faster than if working solely with a SPICE simulation engine.

References

1. März, M., Nance, P., "Thermal Modeling of Power-electronic Systems," February 2000. Available online at www.infineon.com/dgdl/Thermal+Modeling.pdf?fileId=db3a30431441fb5d011472fd33c70aa3..
2. Huang, A., "Infineon OptiMOSTM Power MOSFET Datasheet Explanation," Application Note AN 2012-03 V1.1 March 2012. Available online at www.infineon.com/dgdl/Infineon-MOSFET_Opti-MOS_datasheet_explanation-AN-v01_00-EN.pdf?fileId=db3a30433b47825b013b6b8c6a3424c4.
3. Vuletic, R., Hyde, R., John, D., "Infineon Buck Simscape Example," MathWorks File Exchange, February 2022. Available online at <https://de.mathworks.com/matlabcentral/fileexchange/106925-infineon-buck-simscape-example>.
4. Available online at <https://www.infineon.com/cms/en/product/power/mosfet/automotive-mosfet/iaut300n08s5n012/>
5. mathworks.com/help/physmod/simscape
6. mathworks.com/help/physmod/sps
7. mathworks.com/help/physmod/simscape/get-started-with-simscape-language.html